Title	A measurement of response time for magnetic amplifiers			
Sub Title				
Author	藤田, 廣一(Fujita, Hiroichi)			
Publisher	慶應義塾大学藤原記念工学部			
Publication year	1954			
Jtitle	Proceedings of the Fujihara Memorial Faculty of Engineering Keio University Vol.7, No.27 (1954.) ,p.83(12)- 87(16)			
JaLC DOI				
Abstract	Recently, the magnetic amplifier is used in a automatic control circuit or a computer circuit. Therefore, the response time of the magnetic amplifier has increased its importance and has been measured frequently. Unfortunately the conventional instruments which measure the response time are considerably inconvenient. For example, the electromagnetic oscillograph is used to take a photograph of the load current wave form of the magnetic amplifier and its wave form is integrated. The method described in this paper in order to measure the response time of the magnetic amplifier consists of a simple and reliable electronic device and a cycle counter.			
Notes				
Genre	Departmental Bulletin Paper			
URL	https://koara.lib.keio.ac.jp/xoonips/modules/xoonips/detail.php?koara_id=KO50001004-00070027- 0012			

慶應義塾大学学術情報リポジトリ(KOARA)に掲載されているコンテンツの著作権は、それぞれの著作者、学会または出版社/発行者に帰属し、その権利は著作権法によって 保護されています。引用にあたっては、著作権法を遵守してご利用ください。

The copyrights of content available on the KeiO Associated Repository of Academic resources (KOARA) belong to the respective authors, academic societies, or publishers/issuers, and these rights are protected by the Japanese Copyright Act. When quoting the content, please follow the Japanese copyright act.

A Measurement of Response Time for Magnetic Amplifiers

(Received April 18, 1955)

Hiroichi FUJITA*

Abstract

Recently, the magnetic amplifier is used in a automatic control circuit or a computer circuit. Therefore, the response time of the magnetic amplifier has increased its importance and has been measured frequently. Unfortunately the conventional instruments which measure the response time are considerably inconvenient. For example, the electromagnetic oscillograph is used to take a photograph of the load current wave form of the magnetic amplifier and its wave form is integrated.

The method described in this paper in order to measure the response time of the magnetic amplifier consists of a simple and reliable electronic device and a cycle counter.

I. Introduction

The response time of a magnetic amplifier is defined as the time during which a change of load current or voltage reaches 63 or 95 percent of a total change. And it is represented occasionally in the number of cycles of a c supply voltage.

When the magnetic characteristics of core materials have a rectangular B-H loop, the wave form of the output current exhibits the typical rapid rise as one core saturates at some angle, and exhibits sinusoidal form after saturation. Therefore, if we measure the response time from the peak value of output current, we can not obtain its exact value, so we must measure it from the area of the output wave form.

The device described in this paper is a simple and reliable electronic device with cycle counter and two thyratrons. One of these thyratron is used as a starting switch of a cycle counter, the other is used as to stop it, when the value of load current reaches a specified value (63% or 95% of total change).

The duration of this cycle counter operation is the response time of the magnetic amplifier. In an integrating circuit, a rectifier (1 N 34) is used as a switching circuit to discharge the condenser in every cycle.

* 藤田廣一, Lecturer at Keio University

A Measurement of Response Time for Magnetic Amplifiers



II. Principle of Operation and Description of Circuit.



In the Figure 1, two thyratrons, V_1 and V_2 , are connected in series. The control d-c voltage of the magnetic amplifier is supplied to the control grid of V_1 and makes the V_1 discharge at the initial point of input unit step function. The control grid of V_2 is connected to the integrating circuit which integrates the output current wave form of the magnetic amplifier. The bias voltage of V_2 must be pre-adjusted to be discharged when the integrated wave form reaches the 95% or 63% of the final steady state value.

Then the potential of P increases rapidly at the discharge of V_1 and falls down at the discharge of V_2 , so we can obtain an impulse during the response time of the magnetic amplifier. This impulse is supplied to a control grid of pushpull triodes, which are always supplied several volts of a-c

50 cycles, but are cut off by ample d-c bias voltage. Therefore, the cycle counter operates, with the signal of 50 cycles, only during the time of the impulse which appears at P.

The particular integrating circuit is shown Figure 2, the output wave form of the magnetic amplifier (a) is integrated by resistor $1 \text{ m}\Omega$ and a capacitor $0.1 \mu\text{F}$ as shown in (b). But desired wave form is shown in (c). In this circuit, the only positive wave form is supplied to the cotrol grid of 6 SN 7, as the negative wave form is passed through the rectifier 1 N 34 which is a switch for negative wave form and the integral of positive wave form starts from zero level. As the result, the wave form (d) appears across the grid of 6 SN 7.

In Figure 3, $T_1/2$ amplifies the output wave forms of the magnetic amplifier. $T'_1/2$ and T_2 amplify the integrated







Hiroichi FUJITA

positive wave form. This amplified integrated wave form is supplied to the control grid of the thyratron V_2 . Variable resister VR_1 adjusts the output voltage of the



Fig. 3

0.1µF (600V)	C_{20}	(1000V)	$0.0001 \; \mu \mathrm{F}$
$10 \mu F (350V)$	C_{21}	(50V)	$10 \ \mu F$
$10\mu\mathrm{F}$ (350V)	C_{22}	(600V)	$0.3~\mu F$
$10\mu\mathrm{F}$ ($350\mathrm{V}$)	C_{23}	(1000V)	$0.1 \ \mu F$
$10\mu\mathrm{F}$ (350V)	C_{24}	(50V)	$10 \ \mu F$
$4 \ \mu F$ (500V)	C_{25}	(600V)	$0.1~\mu { m F}$
$4 \ \mu F \ (500V)$	C_{26}	(50V)	$50 \ \mu F$
4 μF (500V)	C_{27}	(300V)	$1\mu\mathrm{F}$
$0.01 \ \mu F (600V)$	C_{28}	(600V)	$0.1~\mu{ m F}$
$0.01 \mu F (600V)$	C_{29}	(600V)	$0.1\mu\mathrm{F}$
		(600V)	$0.01 \ \mu F$
5, 10, 20, 40 K Ω ($\frac{1}{2}$ W)	VR_1	(600V)	$0.01 \ \mu F$
$20K\Omega + 20K\Omega(Vari)$	VR_2	(600V)	$0.001\mu\mathrm{F}$
$+20 \mathrm{K}\Omega$		(600V)	$0.1 \ \mu F$
$50 \mathrm{K}\Omega$ ($\frac{1}{2} \mathrm{W}$)	VR_3	(350V)	$10~\mu { m F}$
50KΩ (//)	VR₄	(350V)	$10 \ \mu F$
1N34	R	(600V)	$0.1 \ \mu F$
		(350 V)	$10 \ \mu F$
		(350 V)	$10 \ \mu F$

R_1	$2 \mathrm{K}\Omega$	(½W)	C_1
R_2	100 KΩ	(//)	C_2
R_{3}	$100 \text{K}\Omega$	(//)	C_{3}
R_4	$1 \text{M} \Omega$	(//)	C ₄
$R_{\mathfrak{s}}$	$2 \mathrm{K} \Omega$	(//)	C_5
R_6	$100 \mathrm{K}\Omega$	(//)	C_6
R_7	$1 \mathbf{M} \Omega$	(//)	C_7
R_8	$2 \mathrm{K} \Omega$	(//)	C_8
R_9	$1 \mathrm{M} \Omega$	(//)	C_9
R_{10}	$250\mathrm{K}\Omega$	(//)	C_{10}
R_{11}	$2 \mathrm{K} \Omega$	(//)	C_{11}
R_{12}	3ΚΩ	(2W)	C_{12}
R_{13}	$5 \mathrm{K} \Omega$	(//)	C_{13}
R_{14}	$5 \mathrm{K}\Omega$	(//)	C_{14}
R_{15}	$50 \mathrm{K}\Omega$	(½W)	C_{15}
R_{15}	$10 \mathrm{K}\Omega$	(//)	C_{16}
R_{17}	$10\mathrm{K}\Omega$	(//)	C_{17}
R_{18}	$10 \mathrm{K}\Omega$	(//)	C_{18}
R_{19}	$3 K \Omega$	(2W)	C_{19}

A Measurement of Response Time for Magnetic Amplifiers

T_1	6 SN 7	T_9	150/60	Ch	2mH
T_2	6 SJ 7	$T_{_{10}}$	150/60		
T ₃	80 BK	V_1	TY 66 G		
T₄	80 BK	V_2	TY66 G		
T_5	80BK	T_{r1}	P. 100V S. 50V,6.3V		
T_6	6N7	T_{r2}	15×2:1		
T_7	80 BK	T_{r_3}	P.100V , S. 350V×2, 5V		
T_8	80	T_{r4}	P. 100V, S. 250V, 5V		

magnetic amplifier so that the amplified wave form does not distort. R_{11} is chosen lower in order to eliminate undesirable voltages such as noise voltage, abnormal peak voltage of swtching shock, etc. R_{12} limits the current of thyratron V_1 and V_2 . Two resistor of R_{13} and R_{14} are connected in series and divide the anode voltage of V_2 because the thyratron V_2 needs high anode voltage (over 100 volts d-c) but the impulse voltage for T_6 does not need so high. The proper grid potential of T_6 at the operation is obtained by subtracting the voltage across R_{14} from the divided voltage by VR_4 .

The impedance of the cycle couter is low. Therefore an impedance matching is done by trnsformer TR_2 whose delay time can be entirely negligible affirmed as the results of experiment. The capacitors C_1 , C_{11} , C_{12} , C_{13} , C_{14} , C_{17} , C_{20} , C_{28} , and C_{29} serve to by-pass any abnomal voltage in the circuit and to keep the device stable.

III. The Method of Measurement

The block diagram for the method of this measurement is shown in Figure 4. At first, we adjust VR_2 to discharge the thyratron V_1 at the initial point of unit function. Then VR_3 is adjusted to discharge the thyratron V_2 when the integrated

wave form reaches the 95% or 63% of the final steady state value. After these two preparations, we supply a step voltage to control winding of a testing magnetic amplifier then the response time is indicated by the cycle counter. If we want to repeat the measurement, we set back the magnetic amplifier to the former state and break the circuit of thyratrons by SW_1 to



86

(15)



The curve in Figure 5 shows the rela tionship between dial degree of VR_2 when V_1 discharges, and the peak value of the amplitude. Figure 6 shows the same relationship for the thyratron V_2 and VR_3 . Figure 7 is the photograph taken by the electromagnetic oscillographs to assure the operation of this device.





IV. Note

The main error of this device depends upon the fluctuation of a-c supply voltage. If the a-c voltage fluctuates during the preset of device and measurement, the error occurs. When the a-c voltage drops down, the characteristics of this device will not be affected too much, but those of the magnetic amplifier will be affected, that is relatively, the preset final value of the device rises. consequently the response time will be measured as longer than the true response time. Therefore, great care must be taken to maintain the a-c supply voltage stable. The biggest limitation of this device is that it can not measure the response time when the load current of the magnetic amplifier falls down.

Acknowledgement

We acknolwledge our indebtedness to Mr. Nakajima and Mr. Kobayashi of Fuji Electric Co. and Mr. Kamo and Bansho, the student of Keio University.